

DATA SHEET

Hall Effect Current Sensor



PN: CHK_HAX15D4

IPN=500-2500A

Feature

- Open- loop
- Capable measurement of currents: DC, AC,pulse with galvanic isolation between primary circuit and secondary circuit.
- Supply voltage: DC $\pm 12\sim 15V$

Advantages

- High accuracy
- Easy installation
- No insertion losses
- Low power consumption
- Wide current measuring range
- High immunity to external interference

Applications

- Inverter applications
- AC/DC variable-speed drive
- Uninterruptible Power Supplies (UPS)
- Switched Mode Power Supplies (SMPS)
- Frequency drive control home appliances



RoHS



Electrical data $T_a=25^\circ C$ $V_c=\pm 15VDC, R_L=1.0K\Omega$

Parameter \ Ref	CHK500 HAX15D4	CHK800 HAX15D4	CHK1000 HAX15D4	CHK1500 HAX15D4	CHK2000 HAX15D4	CHK2500 HAX15D4
Rated input $I_{pn}(A)$	500	800	1000	1500	2000	2500
Measuring range $I_p(A)$	0 ± 1500	0 ± 2400	0 ± 3000	0 ± 4500	0 ± 5500	0 ± 5500
Output voltage $V_o(V)$	$\pm 4.0*(I_p/I_{PN})$					
Load resistance $R_L(K\Omega)$	>1.0					
Supply voltage $V_C(V)$	$(\pm 12\sim \pm 15) \pm 5\%$					
Accuracy $X_G(\%)$	@IPN, $T=25^\circ C$		$< \pm 1.0$			
Offset voltage $V_{OE}(mV)$	@IP=0, $T=25^\circ C$		$< \pm 20$			
Temperature variation of V_{OE} $V_{OT}(mV/^\circ C)$	@IP=0, $-40 \sim +85^\circ C$		$< \pm 1.0$			
Temperature variation of V_{OE} $V_{OT}(mV/^\circ C)$	@IPN, $-40 \sim +85^\circ C$		$< \pm 0.1 \%$			
Hysteresis offset voltage $V_{OH}(mV)$	@IP=0, after $1*I_{PN}$		$< \pm 20$			
Linearity error $\epsilon_r(\%FS)$	< 1.0					

Di/dt accurately followed A/ μ s		> 100
Response time $\tau_a(\mu$ s)	@90% of IPN	<5.0
Power consumption IC(mA)		15
Bandwidth Bw(KHZ)	@-3dB, IPN	DC-20
Insulation voltage Vd(KV)	@50/60Hz, 1min,AC	5.0

General data

Parameter	Value
Operating temperature TA(°C)	-40 ~ +85
Storage temperature TS(°C)	-55 ~ +125
Mass M(g)	450
Plastic material	PBT G30/G15, UL94- V0;
Standards	IEC60950-1:2001
	EN50178:1998
	SJ20790-2000

Dimensions(mm):

	<p style="text-align: center;">Connection</p> <p style="text-align: center;">General tolerance</p> <p>General tolerance: <math>\pm 0.5\text{mm}</math> Primary through-hole: $21 * 64 \pm 0.3$ Connection of Secondary : 2510-04A (Instead of Molex 5045-04A)</p>
--	---

Remarks

- When the current goes through the primary pin of a sensor, the voltage will be measured at the output end.
- Custom design is available for the different rated input current and the output voltage.
- The dynamic performance is the best when the primary hole is fully filled with.
- The primary conductor should be <math>< 100^\circ\text{C}</math>.

WARNING : Incorrect wiring may cause damage to the sensor.