

DATA SHEET

Hall Effect Current Sensor



PN: CHB_AP15D50/100/125

IPN=50~200A

Feature

- Closed- loop (compensated) current transducer
- Capable measurement of currents: DC, AC,pulse with galvanic isolation between primary circuit and secondary circuit.
- Supply voltage: DC $\pm 9\sim 15$ V

Advantages

- High accuracy
- Easy installation
- Low temperature drift
- Optimized response time
- Low power consumption
- High immunity to external interference



RoHS



Applications

- The application of induction cooker
- AC/DC variable-speed drive
- Uninterruptible Power Supplies (UPS)
- Switched Mode Power Supplies (SMPS)
- Inverter applications

Electrical data: (Ta=25°C, Vc= ±15VDC)

Parameter \ Ref	CHB50 AP15D50	CHB100 AP15D50	CHB125 AP15D125	CHB200 AP15D100
Rated input $I_{pn}(A)$	50	100	125	200
Measuring range $I_p(A)$	0~±150	0~±300	0~±375	0~±600
Turns ratio $N_p/N_S (T)$	1:1000	1:2000	1:1000	1:2000
Output current rms $I_S(mA)$	±50*IP/IPN	±50*IP/IPN	±125*IP/IPN	±100*IP/IPN
Secondary coil resistance $R_S (\Omega)$	30	50	30	50
Inside resistance $R_M (\Omega)$	[(VC-0.6V)/ (IS*0.001)]-RS			
Supply voltage $V_C(V)$	(±9~±15) ±5%			
Accuracy $X_G(\%)$	@IPN,T=25°C		< ±0.5	
Offset current $I_{OE}(mA)$	@IP=0,T=25°C		< ±0.2	
Temperature variation of IOE $I_{OT}(mA/°C)$	@IP=0,-40 ~ +85°C		< ±0.005	
Linearity error $\epsilon_r(\%FS)$			< 0.1	
Di/dt accurately followed (A/μs)			> 100	
Response time $t_{ra}(\mu s)$	@90% of IPN		< 1.0	

Power consumption IC(mA)		15+Is
Bandwidth BW(KHZ)	@-3dB,IPN	DC-200
Insulation voltage Vd(KV)	@50/60Hz, 1min,AC	3.0

General data:

Parameter	Value
Operating temperature TA(°C)	-40 ~ +85
Storage temperature TS(°C)	-55~ +125
Mass M(g)	21
Plastic material	PBT G30/G15, UL94- V0;
Standards	IEC60950-1:2001
	EN50178:1998
	SJ20790-2000

Dimensions(mm):

CHB-AP15D50/100	CHB125AP15D125	Connection
		General tolerance
		General tolerance: $\pm 0.5\text{mm}$ Primary through-hole: $10.5 \times 16.2 \pm 0.15\text{mm}</math>Secondary pin: 3pin 0.6 \times 0.65$

Remarks:

- When the current goes through the primary pin of a sensor, the voltage will be measured at the output end.
- Custom design is available for the different rated input current and the output voltage.
- The dynamic performance is the best when the primary hole is fully filled with.
- The primary conductor should be $<100^\circ\text{C}</math>.$

WARNING : Incorrect wiring may cause damage to the sensor.