

DATA SHEET

Hall Effect Current Sensor



PN: CHK_BR5S2

IPN=50-600A

Feature

- Open- loop
- Capable measurement of currents: DC, AC, pulse with galvanic isolation between primary circuit and secondary circuit.
- Supply voltage: DC +5.0V

Advantages

- Easy installation
- No insertion losses
- Low power consumption
- Wide current measuring range
- High immunity to external interference

Applications

- Inverter applications
- AC/DC variable-speed drive
- Uninterruptible Power Supplies (UPS)
- Switched Mode Power Supplies (SMPS)
- Frequency drive control home appliances



RoHS



Electrical data: (Ta=25°C, Vc=+5.0VDC, RL=2KΩ)

| Parameter \ Ref | CHK50 BR5S2 | CHK100 BR5S2 | CHK200 BR5S2 | CHK300 BR5S2 | CHK400 BR5S2 | CHK600 BR5S2 |
|--|--------------------|-----------------|-----------------|-----------------|-----------------|-----------------|
| Rated input Ipn(A) | 50 | 100 | 200 | 300 | 400 | 600 |
| Measuring range Ip(A) | 0~±50 | 0~±100 | 0~±200 | 0~±300 | 0~±400 | 0~±600 |
| Output voltage Vo(V) | 2.500±2.0*(IP/IPN) | | | | | |
| Output voltage Vo(V) | @IP=0,T=25°C | | | 2.500 | | |
| Load resistance RI(KΩ) | >2 | | | | | |
| Supply voltage Vc(V) | +5.0 ±5% | | | | | |
| Accuracy Xg(%) | @IPN,T=25°C | | | < ±1.0 | | |
| Offset voltage Voe(mV) | @IP=0,T=25°C | | | < ±25 | | |
| Temperature variation of VOE Vot(mV/°C) | @IP=0,-40 ~ +85°C | | | < ±1.0 | | |
| Hysteresis offset voltage Voh(mV) | @IP=0,after 1*IPN | | | < ±20 | | |
| Linearity error εr(%FS) | < 1.0 | | | | | |
| Di/dt accurately followed (A/μs) | > 100 | | | | | |
| Response time tra(μs) | @90% of IPN | | | < 3.0 | | |
| Power consumption Ic(mA) | 15 | | | | | |

| | | |
|---------------------------|-------------------|-------|
| Bandwidth Bw(KHZ) | @-3dB,IPN | DC-20 |
| Insulation voltage Vd(Vd) | @50/60Hz, 1min,AC | 2.5 |

General data:

| Parameter | Value |
|-------------------------------|------------------------|
| Operating temperature Ta(°C) | -40 ~ +85 |
| Storage temperature Ts(°C) | -55~ +125 |
| Mass M(g) | 70 |
| Plastic material | PBT G30/G15, UL94- V0; |
| Standards | IEC60950-1:2001 |
| | EN50178:1998 |
| | SJ20790-2000 |

Dimensions(mm):

| | |
|--|--|
| | <p style="text-align: center;">Connection</p> <p style="text-align: center;">General tolerance</p> <p>General tolerance: <math>\pm 0.5\text{mm}</math> Primary through-hole: $10.5 \times 20.5 \pm 0.3$ Connection of secondary : 4 core cable length $L=650\text{mm}$;</p> |
|--|--|

Remarks:

- When the current goes through the primary pin of a sensor, the voltage will be measured at the output end.
- Custom design is available for the different rated input current and the output voltage.
- The dynamic performance is the best when the primary hole is fully filled with.
- The primary conductor should be $<100^\circ\text{C}</math>.$

WARNING : Incorrect wiring may cause damage to the sensor.